



SERIES FF-AM

TYPE: _____
 CATALOGUE #: _____
 NOTES: _____



Self-Powered Fluorescent Fixture with Sealed Nickel- Cadmium Battery

TAMPERPROOF & VANDALPROOF



Application Incorporates the functions of normal area lighting and emergency lighting into one fixture. Ideal for areas such as stairwells, halls and bathrooms where an easily installed, tamper-proof dual purpose fixture is required.

Features

- **CONSTRUCTION:**
 - Housing is constructed of 16 gauge steel and secured with tamper-proof screws. Tamper-proof screw driver is included.
 - Provided with high-impact polycarbonate lens.
 - Surface mounting.
 - Completely self-contained and maintenance-free.
- **BATTERY PACK:**
 - High efficiency battery pack, complete with inverter charger and battery provides emergency power to one lamp in fixture for 90 min.
- **ELECTRONICS:**
 - Fully automatic solid-state charger.
 - Low voltage disconnect prevents overdischarge of battery.
- **CONTROLS:**
 - Pilot light and test switch.
- **POWER REQUIREMENTS:**
 - Battery pack is dual voltage 120/277Vac, 60Hz, 3.5W. Voltage for fluorescent fixture must be specified 120 or 277V and is indicated by complete model number.

Battery

Long life, maintenance-free Nickel-Cadmium
BATTERY WARRANTY:
 Three (3) year full warranty with additional seven (7) years pro-rata.

Warranty

The entire unit shall carry a full three (3) year warranty against defective parts and improper workmanship under normal operation. The battery shall be warranted for an additional seven (7) years pro-rata.


Lamps

Available with sockets for one (1), 20-W, one (1), 34-W, two(2), 20-W or two(2) 34-W T12 lamps, or one (1) or two(2) 32-W T8 lamps supplied by others.

Dimensions And Selection Chart

Dimensions are approximate and subject to change.

MODEL	A	B	C	Lamp Type
FF-AM-1-20-120 FF-AM-1-20-277 FF-AM-2-20-120 FF-AM-2-20-277	24-1/4"	4-1/2"	4-3/8"	F20T12
FF-AM-1-34-120 FF-AM-1-34-277 FF-AM-2-34-120 FF-AM-2-34-277	48-1/4"	4-1/2"	4-3/8"	F34T12
FF-AM-1-32-120 FF-AM-1-32-277 FF-AM-2-32-120 FF-AM-2-32-277	48-1/4"	4-1/2"	4-3/8"	F32T8



Ordering Information

Example: FF-AM-1-20-120

Series	No. of Lamp Sockets	Wattage of Lamps	Voltage of Fixture
FF-AM = series	1 = 1 lamp socket	-20 = 20 watts	-120 = 120 volts



Thomas & Betts