

Lamp Chart

HOW TO USE THIS CHART:

Use the lamp chart when ordering remote lighting fixtures, non-standard lamps or replacement lamps. When ordering non-standard lamps, or lamps for remote fixtures, be sure to select lamps from those listed under the battery voltage of the unit or system powering the lamp.

- **EXAMPLE:** For a remote fixture powered by a 12 volt unit, only those lamps listed under 12 volts in the lamp chart may be used.

BE SURE TOTAL LOAD DOES NOT EXCEED THE 90 MINUTE: WATTAGE CAPACITY OF THE BATTERY, as stated in each respective unit/system selection chart.

- **FOR UNIT EQUIPMENT:**
Replace standard lamp suffix with non-standard lamp suffix.

EXAMPLE: Model 2SN2/L25 comes standard with 6 volt, 25 watt incandescent lamps.




To order with 6 volt, 20 watt halogen lamps, the appropriate model number would be: 2SN2/LH8

- **FOR REPLACEMENT LAMPS:** Order by replacement number.

- **FOR REMOTE FIXTURES:** Include complete lamp suffix as suffix to model number.

EXAMPLE: ELF645 /L9 6
 | |
 Remote Fixture Model No. Lamp Suffix



COMPLETE LAMP SUFFIX MUST BE STATED (which includes voltage designation)

	Unit/System Battery Voltage	Watts	Rated Volts	Lamp Suffix		Replacement Number	Lamp Number	Lumens	
				for Units	add Volt for Remote Fixtures				
DOUBLE CONTACT BAYONET BASE  RP-11 S-8	6 VOLT	13	6	L13	6	570.0020	88	188	
		18	6	L18	6	570.0037	1130	265	
		25	6	L25	6	570.0038	1134	440	
	12 VOLT	6	12	L6	12	570.0068	90	75	
		13	12	L13	12	570.0022	94	189	
		23	12	L25	12	570.0031	1076	402	
	24 VOLT	9	24	L9	24	570.0058	304	75	
		14	24	L14	24	570.0059	306	189	
		18	24	L18	24	570.0060	308	264	
	36 VOLT	28	24	L28	24	570.0061	1638	402	
		6	36	L6	36	570.0069	1224	48	
		25	36	L25	36	570.0084	1054	403	
	120 VOLT	6	120	L6	120	570.0062	6S6	41	
		10	120	L10	120	570.0063	10C7	66	
	BI-PIN HALOGEN LAMPS  T-2 3/4 T-2 1/4	6 VOLT	6	6	LH4	6	580.0012	784	113
			8	6	LH5	6	580.0013	785	163
			10	6	LH7	6	580.0017	787	201
			12	6	LH6	6	580.0011	786	239
20			6	LH8	6	580.0022	788	402	
12 VOLT		8	12	LH8	12	580.0014	774	163	
		12	12	LH3	12	580.0015	783	277	
		14	12	LH9	12	580.0016	789	302	
		20	12	LH2	12	580.0027	782	314	
		6 VOLT	6	6	L5	6	570.0012	939	68
7.2			6	L7	6	570.0026	927	100	
9			6	L9	6	570.0016	908	150	
12 VOLT		8	12	L8	12	570.0032	906	75	
	9	12	L9	12	570.0025	915	138		
	12	12	L12	12	570.0028	912	151		
	18	12	L18	12	570.0029	921	264		
WEDGE BASE INCANDESCENT  T-5 T-3 1/4	6 VOLT	6	6	L5	6	570.0012	939	68	
		7.2	6	L7	6	570.0026	927	100	
		9	6	L9	6	570.0016	908	150	
	12 VOLT	8	12	L8	12	570.0032	906	75	
		9	12	L9	12	570.0025	915	138	



Lamp Chart



PAR36 SEALED BEAM LAMPS — (Available by Special Order)

 SEALED BEAM HALOGEN PAR36	Unit/System Battery Voltage	Watts	Rated Volts	Lamp Suffix/ Lamp Number	Replacement Number	Center Beam Candle Power (CP)	
	 SEALED BEAM INCANDESCENT PAR36	6 VOLT	HALOGEN				
6			6	H7556	550.0022	400	
8			6	H7551	550.0036	550	
10			6	H7552	550.0037	650	
12			6	H7553	550.0019	850	
20		6	H7554	550.0021	1400		
12 VOLT		HALOGEN					
		8	12	H7555	550.0024	550	
		12	12	H7557	550.0025	850	
		37	12	H7616	550.0047	70,000	
6 VOLT	INCANDESCENT						
	8	6	7613	550.0018	400		
	12	6	4042	550.0030	1100		
	18	6	4014	550.0016	1500		
	25	6	4510	550.0017	800		
	30	6	4515	550.0035	5500		
	12 VOLT	INCANDESCENT					
		12	12	4044	550.0026	1110	
		18	12	4414	550.0027	1500	
		25	12	4446	550.0023	400	
		35	12	4406	550.0032	600	
		25	12	25 PAR36 WFL	550.0028	360	
		25	12	25 PAR36 VWFL	550.0050	160	
		50	12	50 PAR36 NSP	550.0043	11,000	
		50	12	50 PAR36 WFL	550.0029	900	

Note: Light output: Stated in candle power or lumens

 HALOGEN MR16	Unit/System Battery Voltage	Watts	Rated Volts	Lamp Suffix		Replacement Number	Center Beam Candle Power (CP)
				for Units	add Volt for Remote Fixtures		
 LED MR16 Shape	6 VOLT	5	6	M5	6	580.0072	110
		6	6	M6	6	580.0074	130
		10	6	M10	6	580.0079	250
	12 VOLT	12	12	M12	12	580.0080	300
		20	12	M20	12	580.0075	600
		35	12	M35	12	580.0083	1300
		50	12	M50	12	580.0076	2100
	24 VOLT	12	24	M12	24	580.0070	300
		20	24	M20	24	580.0077	600
		35	24	M35	24	580.0084	1200
		50	24	M50	24	580.0078	1800
	12 VOLT LED	5*	12	L5	12	580.0063	205

* 3W white LED and 2W to drive engine