

CHC-2LED Series

City of Chicago approved steel LED combination unit



For top or end-mount installations.

Available in single or double face models.

Each unit comes with two adjustable

6V-5W LED heads.

Housing

- Constructed of 20-gauge steel housing with glass panels
- · Cabinet offered in mist white
- White LED lighting source
- Choice of single or double face available

Mounting

- Canopy supplied for top or end-mount
- Universal knockout pattern on back plate for wall mount

Heads

- Each unit comes with two adjustable 6V-5W LED heads
- Each unit provides 280 lumens

Battery

• 6V lead-calcium, maintenance-free, rechargeable battery

Options

• Available with 10W remote capacity on the CHC-2LEDRC model

Electronics

- Low voltage disconnect
- Dual voltage 120/277, 60Hz
- LED indicator light and push-to-test switch

Power consumption chart

Ordering format

| Model | AC | specs | | DC specs |
|-------------|---------------------|-------|--------------|------------------------|
| CHC-2LED | 120VAC, 60Hz, 0.12A | 12W | Lead-calcium | Minimum 120 minutes |
| CHC-2LED | 277VAC, 60Hz, 0.06A | 13W | | |
| CHC-2LED-RC | 120VAC, 60Hz, 0.12A | 12W | | |
| CHC-2LED-RC | 277VAC, 60Hz, 0.06A | 13W | | |

- Automatic solid-state charger recharges battery in 24 hours
- A 2 hour run time in emergency mode


Approvals

- UL listed for damp location 68°F to 122°F (20°C to 50°C)
- Meets UL 924, NFPA 101 Life safety code, NEC, OSHA, local and state codes
- Meets City of Chicago requirements

Warranty

Three-year full warranty (subject to proper installation and maintenance)
 Detailed warranty terms located at: www.lightalarms.com

Dimensions (Dimensions are approximate and subject to change):



Arrow (chevron) designation









a double face panel

NOTE: Wording and chevrons not to scale. For illustration purposes only.

| Series | Heads | Legend color | Legend style | | Options |
|--------|--|--------------------|--|--|--|
| СНС | -2LED = 2 steel round LED heads | R= Red on white | Single face panels #2A= STAIRS (No arrows) #3= EXIT (No arrows) #5A= STAIRS (Arrow right | Double face panels #17A= STAIRS (No arrows) #18= EXIT (No arrows) #23A= STAIRS (Double arrows ←→) #24= EXIT (Double arrows ←→) #20A= STAIRS (Arrow left ←→ and arrow right | Blank= No option RC= 6V-10W remote capacity ¹ |
| Exam | ple: CHC-2LEDI | R#2A | , | → , one arrow on each side) #21= EXIT (Arrow left ← and arrow right → one arrow on each side) | , |

 $^{^{\}mbox{\scriptsize 1}}\mbox{Compatible}$ only with ELF612/LED remote. One double dedicated remote.